




Texas Instruments TI-15 Battery Replacement

Replace the battery of your Texas Instruments TI-15.

Written By: kayla neal



INTRODUCTION



When your calculator's display turns on and right back off, it is time for a new battery. Replacing the battery for the TI-15 will take approximately less than 10 minutes to get you back in business. This guide will show you step-by-step the replacement for a TI-15 battery.



TOOLS:

- [Phillips #0 Screwdriver](#) (1)
 - [iFixit Opening Tools](#) (1)
-

Step 1 — Battery




- With a Y000 screwdriver, loosen the four 1mm Phillips head screws and set them aside.

Step 2




- With an iFixit opening tool, pry apart a total of 3 notches on the top and bottom of the calculator.

Step 3




- Separate the two panels to reveal the calculator's green circuit board.

Step 4




- Using the iFixit opening tool , slide underneath the battery cover until the battery comes out.

Step 5



- Remove the old battery and insert the new battery.

 Properly dispose or recycle the old battery.

This document was last generated on 2017-10-01 05:00:55 AM.